

Newlec Electronic Touch Slave Switch (NL5750A)

The Newlec Electronic Touch Slave Switch (NL5750A) is part of the Newlec family of switches, timers and detectors which save energy and increase convenience in and around your home or business premises.



Product description

The Newlec Electronic Touch Slave Switch (NL5750A) is used for inter-connection with the Newlec Electronic Touch Time Delay Switch Master (NL5740A). Any combination of Slave Switch units can be wired to any Master, giving a variety of activation functions in one area all operating from one central Master (only one Master per circuit). Newlec Slave Switches must be used with the Newlec Master Time Delay Switch. The Slave activates the Master unit. The Slave Switch cannot be used on its own.

Key features

- 16A any load type (requires Newlec Capacitor (NL5750A) for all types of low wattage, in particular LED loads)
- 3 core connection to Master - Live, Switch Live and Trigger required (Switch Live optional if blue ring indicator is not required)
- No Neutral required
- Back lit blue neon indicator ring
- Re-set timing sequence at any time during countdown
- Can be interlinked with any Newlec Slave Switch for multiple switching (one Master must be in circuit)
- Fits into 25mm depth back boxes

Technical details

- 240V AC/50Hz
- 16A lighting load
- CE Marked
- Complies with BS EN 60669, 60669-1, 60669-2-1, 60669-2-3.
- Power consumption 0.5W
- Flame retardant ABS material

Date completed by manufacturer: February 2013